

O B 04

GENERAL

Category: COACH L
Maximum of cameras:
 8 camera

DIMENSIONS

Length: 11 m
Height: 4 m
Width: 2,5 m
 (3,5 m with expander)
Weight: 17 ton

POWER

Voltage: 40 amps 380/400 Volt
 3phase + N / 50h
Connector type: 63 / 125A
 CEE 5pin
IT-net with trafo

SEATING POSITIONS

Production room: 8
Technical: 5
Sound room: 4

VIDEO

CAMERAS

8 HD cam on Triax / Fiber:
 Grass Valley LDX 80/86/86N
 SONY HDC 3500/4300
Wireless: Livetools
Lenses: 14x, 22x, 72x, 86x, 95x,
 100x

VIDEO ROUTER

Imagine VX 3G router
 HD/3G 216*216
VSM System Control software
redundant

VISION MIXER

GVG Kayak 3 ME HD main-frame:
 GVG Kayak 3MEpanel + AUX
inputs: 48
outputs: 48
aux buses: 10
chromakey: 2 floating
 6 x RAMrecorder
 4ch iDPM

VIDEO RECORD REPLAY

6* VTR positions + 4 DVD
2* LSM positions

GRAPHICS

1 Position:
VIZRT, Chyron, ClarityC52

VIDEO CONNECTIVITY

2* Stagebox Broaman 4* bidi
SDI/INTC/AUDIO
12 Externals

VIDEO MONITORING

Production front: 4* PLANAR 46" 8-split Axon
Production Back: 2* Dell Quad-split + KVM
Recording Front : 2* Penta 24" multiviewer + Dell 20" KVM
Vision & engineering: 2* Penta HD2line 24"(8 split) + 2 Ikegami + 2 WFM (Shad 1-2)
 Dell 20" KVM + TEK WVR7000

Sound: 1* Penta HD2line 17" + 2* HP 23" 8-Split

GLUE WARE

Axon SYNAPSE:
 8* Embedders
 4* De-embedders / Framestore/ CCR
 6* Framestore
 4* Crossconvertor
 KVM router Adder 8*8

AUDIO MIXER

LAWO mc² 56 MK II
48 Faders: 16+16C+16
44 Full DSP

AUDIO CONNECTIVITY

1 * Dallis 56 Mic/line in - 16 out - 4 Riedel coax on 2 x MM 2ch Fiberco
1 * Dallis 32 Mic/line in - 16 out - 4 Riedel coax on 2 x MM 2ch Fiberco
1 * External Madi on MM 2ch Fiberco

AUDIO MONITORING

Sound:

Adam S3A 2.0
Auratone se Sound-Cube
4x Fostex

Production:

Genelec 2.0
2x Fostex

AUDIO OUTBOARD

1 * Waves MaxxBCL	1 * 16ch EVS AES3
1 * TC Electronics System 6000 with 8ch in-out with Multichannel mastering	1 * VTR AES3
1 * TC Electronics M5000	1 * Vpro8 madi
1 * Lexicon 480L	1 * Spoton playback software on madi
1 * RTW TM9 8ch AES3/ 1x SDI	1 * Extra Madi in Auditoroom

COMMUNICATION

Intercom matrix:	Riedel Artist 64
Coax Panel ports:	16 * Coax Ports
AES Panel ports	16 * AES Ports
Analog 4wire	24
Madi 4wire	16 to Lawo
Panels Internal	10 * RCP 1028/1012
Panels External	10 * RCP 1028/1012 (4 in Base set)
ISDN/IP Codecs	3 on request
Motorola GM360 basestation (TX/RX)	2
Motorola GP340 Walkie Talkie	6
BOLERO Wireless Intercom	on request